

Remarks

This Preliminary Amendment cancels, without prejudice, claims 1-8 in the underlying PCT Application No. PCT/EP2004/050187 and adds new claims 9-16. The new claims, inter alia, conform the claims to United States Patent and Trademark Office rules and do not add any new matter to the application.


In accordance with 37 C.F.R. § 1.125(b), the Substitute Specification (including Abstract) contains no new matter. The amendments reflected in the Substitute Specification (including Abstract) are to conform the Specification and Abstract to United States Patent and Trademark Office rules or to correct informalities. As required by 37 C.F.R. §§ 1.121(b)(3)(ii) and 1.125(c), a Marked-Up Version of the Substitute Specification comparing the Specification of record and the Substitute Specification also accompanies this Preliminary Amendment. Approval and entry of the Substitute Specification (including Abstract) are respectfully requested.

The underlying PCT Application No. PCT/EP2004/050187 includes an International Search Report, dated June 30, 2004, a copy of which is included. The Search Report includes a list of documents that were considered by the Examiner in the underlying PCT application.

Applicants assert that the subject matter of the present application is new, non-obvious, and useful. Prompt consideration and allowance of the application are respectfully requested.

Respectfully Submitted,

KENYON & KENYON

 (R. No. 36,197)

Dated: 10/7/05

By: JONG LEE for Gerard Messina
Gerard A. Messina
(Reg. No. 35,952)

One Broadway
New York, NY 10004
(212) 425-7200

METHOD FOR ASCERTAINING THE INDIVIDUAL CONTROL VOLTAGE OF A
PIEZOELECTRIC ELEMENT

Background Information

~~The present invention relates to a method for ascertaining the individual control voltage of a piezoelectric element.~~

~~Piezoelectric elements of this kind are used, for example, as piezo injectors in~~

5 injection systems for motor vehicles. They are charged to a specific voltage that is proportional to a lift of the piezoelectric element. Transmitted with the aid of a hydraulic coupler, this lift actuates an injection valve. To ensure the full functionality of such a piezo injector, the control voltage for every operating point, for example in the case of an injection system for a motor vehicle for every pressure in the
10 common-rail system, for every temperature and the like, must be selected in such a way that the control valve opens and remains in the open position for the duration of the injection cycle.

In the method ~~known from~~ described in German Patent Application No. DE 100 32 022 A1, 022, for example, the control voltage, which is individual in every
15 piezoelectric element (individual control voltage), is ascertained by indirectly measuring the pressure in the hydraulic coupler prior to the injection process. From the pressure induced by the hydraulic coupler in the piezo actuator, a corresponding piezo voltage in the actuator is inferred.

20 Furthermore, methods are also known in which the voltage is varied in certain regions and at the same time the injection quantity is measured. The operativeness of the piezoelectric element is inferred from the measured injection quantity.

25 A method and a circuit for the time-dependent measurement of the voltage along a piezoelectric element emerges for example from European Patent Application No. EP 1 138 902 A1, 902.

30 When manufacturing piezo elements that are used in common-rail diesel injection systems, it is necessary to adhere to very narrow tolerances in the manufacture of such piezo common-rail injectors so as to yield the highest possible output in the

series. Very important for this purpose is the interaction between the piezo actuator and the hydraulic system, for example, in the form of the hydraulic coupler. Since in injectors of this kind no sensors can be used for reasons of costs, only little information is available regarding the dynamic behavior of piezo injectors.

Until now, changes of piezo actuators as a result of aging, for example, an aging of the piezo ceramics or the breaking of valve seats, can only be compensated at least partially by previously defined characteristics maps, which are stored for example in a control unit of an internal combustion engine.

The An objective of the present invention is to ascertain, in a manner that is technically as simple as possible and as cost-effective as possible, the individual control voltage of piezo elements, particularly piezo injectors used particularly in diesel common-rail injection systems. In so doing, the dynamics of an individual control voltage, which changes over the service life of a piezo injector, is to be taken into account as well.

Summary of the Of The Invention

This objective is achieved by a method for determining the individual control voltage of a piezoelectric element ~~having the features of Claim 1~~ according to the present invention.

The A basic idea of the present invention is to use the piezo actuator and thus the piezo ceramics itself as a sensor, thereby rendering additional sensors superfluous. Rather, the voltage drop at the piezoelectric element following a charge process is measured and the individual control voltage of the piezoelectric element is inferred from this voltage drop itself.

In a very advantageous specific embodiment of the present invention, the voltage applied at the piezoelectric element is measured immediately following a charge process and the voltage applied at the piezoelectric element is measured immediately before a discharge process following the charge process and are subtracted from each other, and the individual control voltage of the piezoelectric element is inferred from this difference. As a result, a complex and cost-intensive

ascertainment of the individual control voltage, for example by varying the control voltage, may be omitted.

For this purpose, the individual control voltage is advantageously gathered from a characteristic representing the relation between the difference and the individual control voltage.

This characteristic is preferably ascertained experimentally on the basis of a large number of measurements on different piezoelectric elements and is stored for example in a control unit of a motor vehicle.

Another very advantageous refinement of the method provides for the voltage applied at the piezoelectric element during the charge process to be increased iteratively until the voltage applied at the piezoelectric element immediately following the charge process does not deviate from the voltage applied at the piezoelectric element immediately prior to the subsequent discharge process and for the voltage thus ascertained to be rated as the individual voltage requirement.

Another advantageous refinement of the method provides for the piezoelectric element to have only one voltage applied to it and for the charge time to be iteratively increased until the voltage applied at the piezoelectric element immediately following the charge process does not deviate from the voltage applied at the piezoelectric element immediately prior to the discharge process and for the voltage thus ascertained to be rated as the individual control voltage. Preferably, the iterative increase of the voltage applied to the piezoelectric element and the measurement of the voltage at the piezoelectric element immediately prior to the discharge process occur at low pressures of the fluid to be injected. The voltage characteristic is preferably measured continuously at the piezoelectric element.

Brief Description of the DrawingOf The Drawings

Further advantages and features of the present invention are the subject matter of the subsequent specification as well as of the illustrative representation of exemplary embodiments of the present invention.

~~The figures in the drawing show:~~

~~Fig. 1~~ Figure 1 shows the schematic structure of an injection valve known from the related art;

5 ~~Fig. 2~~ Figure 2 shows a schematic representation of the voltage plotted against the control time when charging and discharging a piezoelectric element according to the present invention;

~~Fig. 3~~ Figure 3 shows the relation between the voltage change and the individual
10 control voltage of a piezoelectric element and;

~~Fig. 4~~ Figure 4 shows a schematic representation of temporal voltage characteristics for explaining the measurement of the individual control voltage of a piezoelectric element according to a further exemplary embodiment of the present invention.
15

Detailed Description of preferred exemplary embodiments

Figure 1 shows a schematic representation of an injection valve 1 known from the related art having a central bore hole. In the upper part, an operating piston 3 having a piezoelectric actuator 2 is inserted into the central bore hole, operating piston 3
20 being rigidly connected to actuator 2. Toward the top, operating piston 3 terminates a hydraulic coupler 4, while toward the bottom an opening having a connecting channel to a first seat 6 is provided, in which a piston 5 having a valve closing element 12 is situated. Valve closing element 12 takes the form of a double-closing control valve. It closes first seat 6 if actuator 2 is in the rest phase. When operating
25 actuator 2, that is, when applying a control voltage U_a to the terminals +, -, actuator 2 activates operating piston 3 and via hydraulic coupler 4 pushes piston 5 together with the closing element 12 in the direction of a second seat 7. Below the second seat, a nozzle needle 11 is situated in a corresponding channel, which closes or opens the outlet in a high-pressure channel (common-rail pressure) 13 depending on
30 which control voltage U_a is applied. The high pressure is supplied through the medium to be injected, for example fuel for an internal combustion engine, via an inlet 9, while the inflow quantity of the medium in the direction of nozzle needle 11 and hydraulic coupler 4 is controlled via a inlet throttle 3 and an outlet throttle 10. In this context, the task of hydraulic coupler 4 is to reinforce the lift of piston 5 on the

one hand and on the other to decouple the control valve from the static temperature expansion of actuator 2. The recharging of coupler 4 is not shown here.

The mode of operation of this injection valve will be explained in more detail below.

5 In each triggering of actuator 2, operating piston 3 is moved in the direction of hydraulic coupler 4. In the process, piston 5 together with closing element 12 also moves in the direction of second seat 7. Via a leakage gap, a portion of the medium contained in hydraulic coupler 4, for example fuel, is pressed out in the process. Between two injections, therefore, hydraulic coupler 4 must be refilled to maintain its
10 functional reliability.

A high pressure prevails via inlet channel 9, which in the common-rail system, for example, may amount to between 200 and 2000 bar. This pressure acts against nozzle needle 11 and keeps it closed such that no fuel is able to emerge. If now as a
15 consequence of control voltage U_a , actuator 2 is operated and closing element 12 is thereby moved in the direction of the second seat, then the pressure in the high pressure area decreases and nozzle needle 11 frees the injection channel. P_1 indicates the so-called coupler pressure as it is measured in hydraulic coupler 4. Without control U_a , a stationary pressure P sets in in coupler 4, which, for example,
20 amounts to 1/10 of the pressure in the high-pressure part. Following the discharge of actuator 2, coupler pressure P_1 is approximately 0 and is raised again by recharging.

A change in the length of piezoelectric actuator 2 is achieved by applying a current to piezoelectric actuator 2 in a first time interval Δt_1 . First time interval Δt_1 is the charge
25 process of piezoelectric actuator 2. In this interval, piezoelectric actuator 2 is charged to a maximum voltage U_{max} . The discharge process of the piezoelectric actuator occurs in another time interval Δt_2 (see Figure 2). In a third time interval Δt_3 , lying between these two intervals, piezoelectric actuator 2 acts like a sensor in which any changes in length/force result in changes in voltage. The time characteristic of
30 the voltage during interval Δt_3 now depends on what voltage is applied to piezoelectric actuator 2 immediately following the charge process, that is, at the end of interval Δt_1 . In extensive series of measurements it was determined that the voltage decreases continuously until it asymptotically approaches a voltage, immediately prior to the discharge process, designated in Figure 2 as U_{Regel} .

In an advantageous specific embodiment, the voltage difference ΔU between the maximum voltage U_{\max} and the voltage immediately prior to the discharge process U_{Regel} is now measured. This voltage difference results from the fact that after switching off the charge current, operating piston 3 still travels a distance since piezoelectric actuator 2 expands further. If this voltage difference ΔU is large, for example, then the control valve must still travel a large distance after the charge current has been switched off, which causes the voltage in the sensory region of piezoelectric actuator 2 to drop more considerably since actuator 2 expands further than is the case in an injector in which closing element 12 is already very close to second seat 7 due to operating piston 3. In this case ΔU is small.

Series of measurements have shown that voltage difference ΔU correlates to the individual voltage requirement of the injector. Such piezoelectric actuators 2 therefore require an individual control voltage U_a because the seat diameter, the actuator lift, the friction etc. are subject to deviations that affect the voltage requirement. If the voltage difference ΔU is large, then the voltage requirement of the piezoelectric actuator is greater than in the case of a small voltage difference. Such an injection valve behaves accordingly in temperature changes. If the temperature rises, then the voltage requirement increases and the voltage difference increases accordingly. The individual control voltage U_a is now ascertained by measuring the voltage difference and determining from this, for example on the basis of a characteristic curve as shown in Figure 3, the individual control voltage U_a . Using a single measurement, for example during the flushing process in the mass production of injection valves 1, this makes it possible to determine the individual voltage requirement of the injector.

Another exemplary embodiment of the present invention is explained in more detail below in connection with Figure 4.

In the example shown in Figure 2 - as mentioned above - ball valve 12 at the end of the charge process has not yet arrived at second seat 7. Rather, ball valve 12 continues to move, piezoelectric actuator 2 continues to expand at constant load, which causes the voltage to drop as shown schematically in Figure 2.

Another refinement of the method now provides for voltage U_{\max} to continue to increase continuously until at the end of the discharge process it does not change anymore. For this purpose, the voltage is ideally increased at low pressures in small increments. The injection quantity is hereby influenced only very little such that the operation of injection valve 1 is not disturbed. As soon as voltage U_{\max} applied at the piezoelectric element has assumed a value corresponding to the individual voltage requirement, the voltage no longer changes in interval Δt_3 such that the voltage characteristic assumes the trapezoidal shape shown schematically in Figure 4. In this case, the voltage U_{\max} applied at piezoelectric actuator 2 following the charge process corresponds to the individual voltage requirement which may be stored, for example, in a control unit. A further increase of voltage U_{\max} applied at piezoelectric actuator 2 following the discharge process would now no longer effect any change in the voltage characteristic. From the voltage requirement, it is now possible to ascertain, via a characteristic for example, the individual control voltage, which defined for energetic reasons for example is decreased.

In a further exemplary embodiment, voltage U_{\max} applied to the piezoelectric actuator is kept constant and the charge time, that is, the magnitude of the interval Δt_1 is varied, that is, in particular it is increased by increments in order to ascertain the characteristic point of the voltage, that is, to ascertain the voltage at which the voltage applied at piezoelectric actuator 2 following the charge process practically does not change any more in interval Δt_3 .

In all of the refinements of the method according to the present invention described above it is advantageous that the individual control voltage U_a may be ascertained without additional sensors and that moreover it also allows for conclusions regarding the dynamic behavior of injection valve 1 during its operation, for if, for example, the injection valve is operated at the characteristic point, that is, at the point when the voltage U_{\max} applied at the piezoelectric actuator 2 following the discharge process does not change anymore, it is ensured that ball valve 12 has reached second seat 7.

Abstract Of The Disclosure

An a method for ascertaining the control voltage of a piezoelectric element is characterized by the fact that, the voltage drop at the piezoelectric element following a charge process is measured and the control voltage of the piezoelectric element is

5 inferred from this voltage drop.